

ZIGBEE DIMMER MODULE RECEIVER

ZIGBEE 3.0

ZBCMR-300





ZIGBEE DIMMER MODULE RECEIVER

ZIGBEE 3.0

ZigBee dimmer module receiver, controlled by control panel app, wired wall switch or directly by ZigBee remote, it can make traditional lighting and appliances device smart, and make the device work on schedule.

Voice control and compatible with Amazon Alexa and Google Assistance.

ZigBee dimmer module receiver can be used as range extender, resulting in a more stable connection over longer distances.

FEATURES

- ZigBee dimmer module based on latest ZigBee 3.0 protocol.
- Simple Join Mode application or TouchLink commissioning.
- Supports self-forming Zigbee network without coordinator.
- Control mode under Trailing Edge, Leading Edge and Filament LED bulb mode selection.
- Minimum brightness setup for different kinds of dimmer outputs.
- Fits into standard wall box.
- Use in conjunction with standard wired rocker wall switch.

TECHNICAL DATA

- Input Rating: 230V~50Hz
- Output Rating:
3W ~ 24W Max. LED
300W Max. Incandescent Lamp
- Radio Frequency: 2.4GHz
- Power Consumption: <1W
- Environment Temperature: 0-40 °C
- Range: Up to 50 Meter range (Depends on building materials.)

SPECIFICATION

- Dimension (W x H x D): 47 x 47 x 18 mm
- Weight: 20g