



200M DC DOOR CHIME SET

LMLT-711 + MLR-1105



Doorbell Push Button:

- IP44 weather / water-resistant.
- Red LED rim around the push button.
- Battery low indication and sound warning.
- 2 years battery life.

Door Chime:

- Blue LED indicator.
- 5 selectable ringtones.
- High – Medium – Low volume.
- Mute mode with blue flashing strobe light effect.
- Battery low indication.
- 2 years battery life.

200M DC PUSH BUTTON & DOOR CHIME

Offering easy installation and reaching up to 200 meters, the advanced new battery-operated Wireless Door Chime and Doorbell Push Button helps you feel secure in your home. This door chime features clearly audible ringtones and flashing light that make it easy to know when someone is at your door. Mobility, place it anywhere or fix it permanently with the easy wall mount bracket. Door chime can be connected with up to 4 doorbell push buttons / transmitters such as entry sensor and motion sensor simultaneously. Each transmitter can learn with the door chime with different ringtone as doorbell sound or an alert sound.

i FEATURES

- Compatible to L and M series.
- IP44 weather / water-resistant push button.
- Up to 200 meters open field.
- 4 memories..

⚙️ TECHNICAL DATA

- Battery:
 - 3V CR2032 Lithium Cell Battery (Push Button)
 - 3 x 1.5VDC (AA) Alkaline Battery (Door Chime)
- Radio Frequency: 433.92MHz
- Environment Temperature: 0-40 °C
- Range: Up to 200 Meter range (Open Field).
- Speaker Decibel: 76dB Max.

⚙️ SPECIFICATION

- Dimension: 70 x 30 x 15 mm (Push Button)
68 x 65 x 108 (Door Chime)
- Weight: 35g (Push Button) 120g (Door Chime)